

V.M. Red'kov¹, N.G. Tokarevskaya, V.V. Kisel

**On the theory of a scalar particle with electromagnetic polarizability
in Coulomb and Dirac monopole fields**

Institute of Physics of National Academy of Sciences of Belarus
Belarus State Pedagogical University of M.Tank

15-component matrix and tetrad-based description of a scalar particle with two electromagnetic characteristics – charge e and polarizability σ , is elaborated in presence of external Coulomb field. With the use of Wigner's D -functions technics, in the basis of diagonal spherical tetrad, the separation of variables in the generalized wave equation is done, and a system of 15 radial equations is given. It is shown that all the radial system is reduced to a generalized Klein-Fock radial equation with an additional term of the form $\sigma(e^4/M^2 r^4)$. In the framework of the analogous approach a scalar particle with charge e and polarizability σ is investigated in presence of the field of a magnetic charge g . The separation of variables is done. Again all the radial system is reduced to a single differential equation of second order with an additional term of the form $\sigma(e^2 g^2/M^2 r^4)$. This means that because of the known peculiar properties of the potential r^{-4} (an absorbing center), the monopole influence on the scalar particle with σ -characteristics is much more noticeable in the radial equation than in the case of usual scalar particle with a charge only.

Keywords: Coulomb field, Dirac monopole, electromagnetic interaction, polarizability.
PACS numbers: 1130, 0230, 0365

1 Introduction

This work continues study of the 15-component theory of a charged scalar particle with additional electromagnetic characteristic – polarizability [1-10] now turning to behavior of such a particle in Coulomb and Dirac magnetic monopole fields.

Initial system of generalized equations for a free scalar particle of the mass $m = -iMc/\hbar$ has the form

$$\begin{aligned} \lambda_1 \partial^a \Phi_{1a} + \lambda_2 \partial^a \Phi_{2a} - m \Phi &= 0, \\ \lambda_1^* \partial_a \Phi + \lambda_3 \partial^b \Phi_{ba} - m \Phi_{1a} &= 0, \\ -\lambda_2^* \partial_a \Phi + \lambda_4 \partial^b \Phi_{ba} - m \Phi_{2a} &= 0, \\ \pm \lambda_3^* (\partial_a \Phi_{1b} - \partial_b \Phi_{1a}) \mp \lambda_4^* (\partial_a \Phi_{2b} - \partial_b \Phi_{2a}) - m \Phi_{ab} &= 0. \end{aligned} \tag{1}$$

Here Φ stands for a scalar, Φ_{1a} and Φ_{2a} represent two 4-vectors, and Φ_{ab} is anti-symmetrical tensor. Latin indices take on the values 0, 1, 2, 3. In the flat Minkowski space the metric

¹E-mail: redkov@dragon.bas-net.by

tensor $(g_{ab}) = \text{diag}(+1, -1, -1, -1)$ is used. Field functions $\Phi, \Phi_{1a}, \Phi_{2a}, \Phi_{ab}$ are assumed to be complex-valued; therefore they describe a charged scalar particle.

One should take attention to the following fact: because of complex-valued parameters $\lambda_1, \dots, \lambda_4$ separating in eqs. (1) the corresponding theory for scalar particle without electric charge will require special treatment – this task will be solved bellow. From previous works [1,2] it is known that four parameters λ_i can be chosen differently – it is essential only that they obey two conditions

$$\lambda_1 \lambda_1^* - \lambda_2 \lambda_2^* = 1, \quad \lambda_3 \lambda_3^* - \lambda_4 \lambda_4^* = 0. \quad (2)$$

The above equations (1) can be rewritten in a matrix form (15-component vector-column $\Psi = (\Phi, \Phi_{1a}, \Phi_{2a}, \Phi_{ab})$)

$$\begin{aligned} & (\Gamma^a \partial_a - m) \Psi = 0, \\ \Gamma^a = & \begin{vmatrix} 0 & \lambda_1 G^a & \lambda_2 G^a & 0 \\ \lambda_1^* \Delta^a & 0 & 0 & \lambda_3 K^a \\ -\lambda_2^* \Delta^a & 0 & 0 & \lambda_4 K^a \\ 0 & \pm \lambda_3^* \Lambda^a & \mp \lambda_4^* \Lambda^a & 0 \end{vmatrix}, \end{aligned} \quad (3)$$

where four basic matrices Γ^a are expressed in terms of blocks: $G^a, K^a, \Delta^a, \Lambda^a$ of dimension $1 \times 4; 4 \times 1; 4 \times 6; 6 \times 4$ respectively:

$$\begin{aligned} (G^a)_{(0)}^k &= g^{ak}, \quad (\Delta^a)^{(0)}_n = \delta_n^a, \\ (K_a)_n^{kl} &= g^{ak} \delta_n^l - g^{al} \delta_n^k, \\ (\Lambda^a)^k_{nb} &= \delta_{nb}^{ak} = \delta_n^a \delta_b^k - \delta_n^k \delta_b^a. \end{aligned} \quad (4)$$

One can perform, special linear transformation over the wave function $\Psi' = S\Psi$, such that a new equation for Ψ' does not contain any complex-valued quantities. The transformation with required properties can be factorized as follows: $\Psi' = S\Psi = S_2 S_1 \Psi$, where

$$\begin{aligned} \Psi' = & \begin{vmatrix} \Phi \\ \Phi_a \\ C_a \\ C_{ab} \end{vmatrix}, \quad S_1 = \begin{vmatrix} 1 & 0 & 0 & 0 \\ 0 & \lambda_1 & \lambda_2 & 0 \\ 0 & \lambda_3^* & -\lambda_4^* & 0 \\ 0 & 0 & 0 & I \end{vmatrix}, \\ S_2 = & \begin{vmatrix} d^* & 0 & 0 & 0 \\ 0 & d^* & 0 & 0 \\ 0 & 0 & I & 0 \\ 0 & 0 & 0 & I \end{vmatrix}, \quad d = \lambda_1 \lambda_3 + \lambda_2 \lambda_4, \end{aligned} \quad (5)$$

here separate components of Ψ' are designated by $\Phi, \Phi_a, C_a, C_{ab}$. In terms of these constituents eqs. (1) take the form

$$\begin{aligned} & \partial^a \Phi_a - m \Phi = 0, \\ & \partial_a \Phi + \sigma \partial^b C_{ba} - m \Phi_a = 0, \\ & \partial_a \Phi - m C_a = 0, \\ & \pm (\partial_b C_a - \partial_a C_b) - m C_{ba} = 0. \end{aligned} \quad (6)$$

On should take notice that now all dependence on λ_i -parameters in the wave equations (6) is realized through only real-valued characteristic $\sigma = dd^*$. Again eqs. (6) can be expressed as one matrix relationship

$$\begin{aligned} & (\Gamma'^a \partial_a - m) \Psi' = 0, \\ \Gamma'^a = & \begin{vmatrix} 0 & G^a & 0 & 0 \\ \Delta^a & 0 & 0 & \sigma K^a \\ \Delta^a & 0 & 0 & 0 \\ 0 & 0 & \pm \Lambda^a & 0 \end{vmatrix}. \end{aligned} \quad (7)$$

The favored feature of this basis is that now C -operation is reduced to only complex conjugation $\Psi'^{(c)} = C'(\Psi')^* = \Psi'^*$.

Now we should dwell upon some peculiarities of that generalized theory of a scalar particle in presence of electromagnetic fields. The presence of such external fields $A_a(x)$ can be taken into account through extension of the derivative: $\partial_a \implies D_a = \partial_a - i\frac{e}{\hbar c} A_a$, , where e stands for a particle charge. Then eqs. (6) will take on the form

$$\begin{aligned} D^a \Phi_a &= m \Phi, \\ D^a \Phi + \sigma D^b C_{ba} &= m \Phi_a, \\ D_a \Phi &= m C_a, \\ \pm (D_b C_a - D_a C_b) &= m C_{ba}. \end{aligned} \quad (8)$$

Between components of the wave function one can pick up the main ones Φ , Φ_a and two auxiliary C_a , C_{ab} . Excluding both auxiliary ones from equation:

$$C_a = \frac{1}{m} \partial_a \Phi, \quad C_{ab} = \mp \frac{ie\sigma}{m^2 \hbar c} F_{ba} \Phi \quad (9)$$

($F_{ab} = \partial_a A_b - \partial_b A_a$ stands for electromagnetic field tensor) one arrives at the following equations for Φ and Φ_a :

$$\begin{aligned} D^a \Phi_a &= m \Phi, \\ D_a \Phi \mp \frac{ie\sigma}{m^2 \hbar c} D^b (F_{ba} \Phi) &= m \Phi_a. \end{aligned} \quad (10)$$

Thus, in the frames of extended theory of a scalar particle, they describe a particle that besides of the electrical charge carries an additional electromagnetic characteristic. In a free particle case this additional characteristic σ does not manifest itself in the main equations (10) and auxiliary constituents satisfy conditions

$$C_a(x) = \Phi_a(x), \quad C_{ab}(x) = 0. \quad (11)$$

Now we briefly outline extension of the above theory to general relativity. In accordance with the known procedure by Tetrad-Weyl-Fock-Ivanenko [11-14] matrix equation (7) is to be replaced by

$$[\Gamma^\alpha(x) (\partial_\alpha + B_\alpha(x)) - m] \Psi(x) = 0, \quad (12)$$

$$\Gamma^\alpha = \Gamma^a e_{(a)}^\alpha, \quad B_\alpha = \frac{1}{2} J^{ab} e_{(a)}^\beta \nabla_\alpha (e_{(b)\beta}). \quad (13)$$

Where $e_{(a)}^\alpha(x)$ is a tetrad a curved space-time with metric tensor $g_{\alpha\beta}(x)$; J^{ab} — stands for generators of the given representation $(\Phi, \Phi_k, C_k, C_{kl})$ of the Lorentz group:

$$J^{ab} = \begin{vmatrix} 0 & 0 & 0 & 0 \\ 0 & V^{ab} & 0 & 0 \\ 0 & 0 & V^{ab} & 0 \\ 0 & 0 & 0 & (V \otimes V)^{ab} \end{vmatrix}.$$

Because equation (12) contains a tetrad explicitly, there must exist definite connection between two different tetrads-based representations, otherwise eq. (12) is incorrect. Such a symmetry of generally covariant equation can be readily proved (all details are omitted here): equations based on two different tetrads related to each other by $e' = L(x)e$ can be transformed to each other by means of a local (15×15) -gauge matrix

$$\Psi'(x) = S(x) \Psi(x), \quad \begin{vmatrix} \Phi' \\ \Phi'_k \\ C'_k \\ C'_{kl} \end{vmatrix} = \begin{vmatrix} 1 & 0 & 0 & 0 \\ 0 & L_k^l & 0 & 0 \\ 0 & 0 & L_k^l & 0 \\ 0 & 0 & 0 & L_k^m L_l^n \end{vmatrix} \begin{vmatrix} \Phi \\ \Phi_l \\ C_l \\ C_{mn} \end{vmatrix}. \quad (14)$$

It can be shown that equation (12) can be reverted to a tensor form:

$$\begin{aligned} \nabla_\alpha \Phi^\alpha - m\Phi &= 0, \\ \nabla_\alpha \Phi + \sigma \nabla^\beta C_{\beta\alpha} - m\Phi_\alpha &= 0, \\ \nabla_\alpha \Phi - mC_\alpha &= 0, \\ \pm (\nabla_\beta C_\alpha - \nabla_\alpha C_\beta) - mC_{\beta\alpha} &= 0. \end{aligned} \quad (15)$$

Here ∇_α stands for a generally covariant derivative. Connection between constitutions of Ψ in (12) and those in (15) looks as follows

$$\Phi_\alpha = e_\alpha^{(l)} \Phi_l, \quad C_\alpha = e_\alpha^{(l)} C_l, \quad C_{\alpha\beta} = e_\alpha^{(m)} e_\beta^{(n)} C_{mn}.$$

It should be added that equations (9) and (10) will be in effect in Riemannian space as well, with only formal change of the usual derivatives into covariant ones. Any specific gravitational interaction terms do not arise here, but in case of any space with non-zero torsion such a term would be.

2 Basic equation and notation

Let us consider equation (12) in spherical coordinates of flat Minkowski space $(x^\alpha = (ct, r, \theta, \phi))$

$$\begin{aligned} dS^2 &= c^2 dt^2 - dr^2 - r^2(d\theta^2 + \sin^2 \theta d\phi^2), \\ g_{\alpha\beta} &= \begin{vmatrix} 1 & 0 & 0 & 0 \\ 0 & -1 & 0 & 0 \\ 0 & 0 & -r^2 & 0 \\ 0 & 0 & 0 & -r^2 \sin^2 \theta \end{vmatrix} \end{aligned} \quad (16)$$

and in the diagonal spherical tetrad

$$\begin{aligned} e_{(0)}^\alpha &= (1, 0, 0, 0) , \quad e_{(3)}^\alpha = (0, 1, 0, 0) , \\ e_{(1)}^\alpha &= (0, 0, \frac{1}{r}, 0) , \quad e_{(2)}^\alpha = (1, 0, 0, \frac{1}{r \sin \theta}) . \end{aligned} \quad (17)$$

With the use of explicit form of the tetrad and the Ricci coefficients we get to the following generalized matrices $\Gamma^\alpha(x)$ and connection $B_\alpha(x)$:

$$\begin{aligned} \Gamma^\alpha(x) &= (\Gamma^0, \Gamma^3, \frac{1}{r} \Gamma^1, \frac{1}{r \sin \theta} \Gamma^2) , \quad B_0 = 0 , \\ B_r &= 0, \quad B_\theta = J^{31} , \quad B_\phi = \sin \theta J^{32} + \cos \theta J^{12} . \end{aligned}$$

Equation (6) will take the form

$$\left[\Gamma^0 \partial_0 + \Gamma^3 \partial_r + \frac{\Gamma^1 J^{31} + \Gamma^2 J^{32}}{r} + \frac{\Sigma_{\theta, \phi}}{r} - m \right] \Psi = 0 \quad (18)$$

where $\Sigma_{\theta, \phi}$ stands for an angular operator

$$\Sigma_{\theta, \phi} = \Gamma^1 \partial_\theta + \Gamma^2 \frac{\partial_\phi + \cos \theta J^{12}}{\sin \theta} . \quad (19)$$

In the following we will need explicit form of all matrices involved. With the use of the notation

$$\begin{aligned} \vec{e}_1 &= (1, 0, 0) , \quad \vec{e}_2 = (0, 1, 0) , \quad \vec{e}_3 = (0, 0, 1) , \\ \vec{e}_1^t &= \begin{vmatrix} 1 \\ 0 \\ 0 \end{vmatrix} , \quad \vec{e}_2^t = \begin{vmatrix} 0 \\ 1 \\ 0 \end{vmatrix} , \quad \vec{e}_3^t = \begin{vmatrix} 0 \\ 0 \\ 1 \end{vmatrix} , \\ \tau_1 &= \begin{vmatrix} 0 & 0 & 0 \\ 0 & 0 & -1 \\ 0 & 1 & 0 \end{vmatrix} , \quad \tau_2 = \begin{vmatrix} 0 & 0 & 1 \\ 0 & 0 & 0 \\ -1 & 0 & 0 \end{vmatrix} , \quad \tau_3 = \begin{vmatrix} 0 & -1 & 0 \\ 1 & 0 & 0 \\ 0 & 0 & 0 \end{vmatrix} \end{aligned} \quad (20)$$

the matrices Γ^a are

$$\Gamma^0 = \begin{vmatrix} 0 & 1 & \vec{0} & 0 & \vec{0} & \vec{0} & \vec{0} \\ 1 & 0 & \vec{0} & 0 & \vec{0} & \vec{0} & \vec{0} \\ \vec{0}^t & \vec{0}^t & 0 & \vec{0}^t & 0 & -\sigma I & 0 \\ 1 & 0 & \vec{0} & 0 & \vec{0} & \vec{0} & \vec{0} \\ \vec{0}^t & \vec{0}^t & 0 & \vec{0}^t & 0 & 0 & 0 \\ \vec{0}^t & \vec{0}^t & 0 & \vec{0}^t & \pm I & 0 & 0 \\ \vec{0}^t & \vec{0}^t & 0 & \vec{0}^t & 0 & 0 & 0 \end{vmatrix} ,$$

$$= \begin{vmatrix} 0 & 0 & -\vec{e}_i & 0 & \vec{0} & \vec{0} & \vec{0} \\ 0 & 0 & \vec{0} & 0 & \vec{0} & -\sigma \vec{e}_i & \vec{0} \\ \vec{e}_i^t & \vec{0}^t & 0 & \vec{0}^t & 0 & 0 & -\sigma \tau_i \\ 0 & 0 & \vec{0} & 0 & \vec{0} & \vec{0} & \vec{0} \\ \vec{e}_i^t & \vec{0}^t & 0 & \vec{0}^t & 0 & 0 & 0 \\ \vec{0}^t & \vec{0}^t & 0 & \mp \vec{e}_i^t & 0 & 0 & 0 \\ \vec{0}^t & \vec{0}^t & 0 & \vec{0}^t & \pm \tau_i & 0 & 0 \end{vmatrix}.$$

We will need explicit form of generators

$$J^{ab} = \begin{vmatrix} 0 & 0 & 0 & 0 \\ 0 & V^{ab} & 0 & 0 \\ 0 & 0 & V^{ab} & 0 \\ 0 & 0 & 0 & (V \otimes V)^{ab} \end{vmatrix},$$

where

$$(V^{ab})_k^l = -g^{al} \delta_k^b + g^{bl} \delta_k^a,$$

$$(V^{23})_k^l = \begin{vmatrix} 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & -1 \\ 0 & 0 & 1 & 0 \end{vmatrix} = \begin{vmatrix} 0 & 0 \\ 0 & \tau_1 \end{vmatrix},$$

and so on. Also

$$[(V \otimes V)^{ab}]_{mn}^{sp} = (-g^{as} \delta_m^b + g^{bs} \delta_m^a) \delta_n^p + \delta_m^s (-g^{ap} \delta_n^b + g^{bp} \delta_n^a),$$

where index combinations 01, 02, 03, 23, 31, 12 are used; further

$$[(V \otimes V)^{23}]_{mn}^{sp} = \begin{vmatrix} \tau_1 & 0 \\ 0 & \tau_1 \end{vmatrix}, \text{ and so on.}$$

The total momentum operator (the sum of orbital and spin ones) has in Cartesian coordinates the ordinary form

$$J_k = l_k + S_k,$$

$$S_1 = iJ^{23}, S_2 = iJ^{31}, S_3 = iJ^{12},$$

$$S_k = i [0 \oplus (0 \oplus \tau_k) \oplus (0 \oplus \tau_k) \oplus (\tau_k \oplus \tau_k)]. \quad (21)$$

Now we are to determine the form of J_k -operators in spherical tetrad basis. Two tetrads are related to each other by means of the law (see (14))

$$e'_{(a)}^\alpha = \frac{\partial x'^\alpha}{\partial x^\beta} L_a^b e_{(b)}^\beta,$$

where $e'_{(a)}^\alpha$ is the spherical tetrad, $e_{(b)}^\beta$ is the Cartesian one. Here, the Lorentz matrix is reduced to a pure rotation

$$O_i^j = \begin{vmatrix} \cos \theta \cos \phi & \cos \theta \sin \phi & -\sin \theta \\ -\sin \phi & \cos \phi & 0 \\ \sin \theta \cos \phi & \sin \theta \sin \phi & \cos \theta \end{vmatrix}. \quad (22)$$

Connection between Cartesian wave function Ψ and spherical one Ψ' looks as

$$\Psi'(x) = S \Psi(x), \\ S(\theta, \phi) = [1 \oplus (1 \oplus O) \oplus (1 \oplus O) \oplus (O \oplus O)].$$

With the use of the matrix $S(\theta, \phi)$ one transforms operators

$$J_i = l_i + S_i, \quad J'_a = S J_a S^{-1}.$$

Taking into account the known definitions

$$l_1 = i (\sin \phi \partial_\theta + \operatorname{ctg} \theta \cos \phi \partial_\phi), \\ l_2 = i (-\cos \phi \partial_\theta + \operatorname{ctg} \theta \sin \phi \partial_\phi), \quad l_3 = -i \partial_\phi,$$

and straightforwardly derived relations

$$O i \partial_\theta O^{-1} = i \tau_2, \\ O i \partial_\phi O^{-1} = i (\cos \theta \tau_3 - \sin \theta \tau_1)$$

for $l'_a = O l_a O^{-1}$ one gets:

$$l'_1 = l_1 - i(\cos \theta \cos \phi \tau_1 + \sin \phi \tau_2 + \frac{\cos^2 \theta}{\sin \theta} \cos \phi \tau_3), \\ l'_2 = l_2 - i(\cos \theta \sin \phi \tau_1 - \cos \phi \tau_2 + \frac{\cos^2 \theta}{\sin \theta} \sin \phi \tau_3), \\ l'_3 = l_3 + i(\sin \phi \tau_1 - \cos \theta \tau_3).$$

In the same manner, for $\tau'_a = O \tau_a O^{-1}$ we have

$$\tau'_1 = \cos \theta \cos \phi \tau_1 - \sin \phi \tau_2 + \sin \theta \cos \phi \tau_3, \\ \tau'_2 = \cos \theta \sin \phi \tau_1 - \cos \phi \tau_2 + \sin \theta \sin \phi \tau_3, \\ \tau'_3 = -\sin \phi \tau_1 + \cos \theta \tau_3.$$

Thus we arrive at the final formulas J'_a :

$$J'_1 = l_1 + \frac{\cos \phi}{\sin \theta} S_3, \quad J'_2 = l_2 + \frac{\sin \phi}{\sin \theta} S_3, \\ J'_3 = l_3, \quad \vec{J}'^2 = -\frac{1}{\sin \theta} \partial_\theta \sin \theta \partial_\theta + \frac{-\partial_\phi^2 + 2 i \partial_\phi S_3 \cos \theta + S_3^2}{\sin^2 \theta}. \quad (23)$$

For the following, it will be convenient to have the S_3 -matrix in diagonal form. To this end one needs τ_i -basis to be cyclic one [15]:

$$\Psi'' = U\Psi',$$

$$U = 1 \oplus (1 \oplus U_3) \oplus (1 \oplus U_3) \oplus (U_3 \oplus U_3),$$

where

$$U_3 = \begin{vmatrix} -1/\sqrt{2} & i/\sqrt{2} & 0 \\ 0 & 0 & 1 \\ 1/\sqrt{2} & i/\sqrt{2} & 0 \end{vmatrix}, \quad U_3^{-1} = U_3^+ = \begin{vmatrix} -1/\sqrt{2} & 0 & 1/\sqrt{2} \\ -i/\sqrt{2} & 0 & -i/\sqrt{2} \\ 0 & 1 & 0 \end{vmatrix}.$$

One easily derives

$$U_3\tau_1U_3^{-1} = \frac{1}{\sqrt{2}} \begin{vmatrix} 0 & -i & 0 \\ -i & 0 & -i \\ 0 & -i & 0 \end{vmatrix} = \tau'_1,$$

$$U_3\tau_2U_3^{-1} = \frac{1}{\sqrt{2}} \begin{vmatrix} 0 & -1 & 0 \\ 1 & 0 & -1 \\ 0 & 1 & 0 \end{vmatrix} = \tau'_2,$$

$$U_3\tau_3U_3^{-1} = -i \begin{vmatrix} +1 & 0 & 0 \\ 0 & 0 & 0 \\ 0 & 0 & -1 \end{vmatrix} = \tau'_3.$$

In this cyclic basis, the S_3 matrix is diagonal

$$S_3 = \text{diag} (0; 0, 1, 0, -1; 0, 1, 0, -1; 1, 0, -1; 1, 0, -1) \quad (24)$$

as required. Also we will need explicit "cyclic" vector $\vec{e}_i$ and $\vec{e}_i^t$:

$$\vec{e}_1 = (-\frac{1}{\sqrt{2}}, 0, \frac{1}{\sqrt{2}}), \quad \vec{e}_2 = (-\frac{i}{\sqrt{2}}, 0, -\frac{i}{\sqrt{2}}), \quad \vec{e}_3 = (0, 1, 0), \quad (25)$$

$$\vec{e}_1^t = \begin{vmatrix} -\frac{1}{\sqrt{2}} \\ 0 \\ \frac{1}{\sqrt{2}} \end{vmatrix}, \quad \vec{e}_2^t = \begin{vmatrix} \frac{i}{\sqrt{2}} \\ 0 \\ \frac{i}{\sqrt{2}} \end{vmatrix}, \quad \vec{e}_3^t = \begin{vmatrix} 0 \\ 1 \\ 0 \end{vmatrix}.$$

3 Separation of variables, radial equations

Now we are ready to separate the variables in equation (18). All matrices are assumed to be referred to chosen spherical and cyclic basis, but any reminding of this will be omitted in the designation below. Let the wave function $\Psi(x)$ be taken in the form

$$\Psi(x) = \{ C(x), C_0(x), \vec{C}(x), \Phi_0(x), \vec{\Phi}(x), \vec{E}(x), \vec{H}(x) \}. \quad (26)$$

After simple calculation with the use of block structure of matrices involved we get to the system

$$\begin{aligned}
& \partial_0 C_0 - \vec{e}_3 \partial_r \vec{C} - \frac{1}{r} (\vec{e}_1 \tau_2 - \vec{e}_2 \tau_1) \vec{C} \\
& - \frac{1}{r} (\vec{e}_1 \partial_\theta + \vec{e}_2 \frac{\partial_\phi + \tau_3 \cos \theta}{\sin \theta}) \vec{C} = mC , \\
& \partial_0 C - \sigma \vec{e}_3 \partial_r \vec{E} - \frac{\sigma}{r} (\vec{e}_1 \tau_2 - \vec{e}_2 \tau_1) \vec{E} \\
& - \frac{\sigma}{r} (\vec{e}_1 \partial_\theta + \vec{e}_2 \frac{\partial_\phi + \tau_3 \cos \theta}{\sin \theta}) \vec{E} = mC_0 , \\
& -\sigma \partial_0 \vec{E} + \vec{e}_3^t \partial_r C \\
& -\sigma \tau_3 \partial_r \vec{H} - \frac{\sigma}{r} (\tau_1 \tau_2 - \tau_2 \tau_1) \vec{H} \\
& + \frac{1}{r} (\vec{e}_1^t \partial_\theta + \vec{e}_2^t \frac{\partial_\phi}{\sin \theta}) C \\
& + \frac{\sigma}{r} (\tau_1 \partial_\theta + \tau_2 \frac{\partial_\phi + \tau_3 \cos \theta}{\sin \theta}) \vec{H} = m\vec{C} , \\
& \partial_0 C = m\Phi_0 , \\
& \vec{e}_3^t \partial_r C + \frac{1}{r} (\vec{e}_1^t \partial_\theta + \vec{e}_2^t \frac{\partial_\phi}{\sin \theta}) C = m\vec{\Phi} , \\
& (\pm) [\partial_0 \vec{\Phi} - \vec{e}_3^t \partial_r \Phi_0 \\
& - \frac{1}{r} (\vec{e}_1^t \partial_\theta + \vec{e}_2^t \frac{\partial_\phi}{\sin \theta}) \Phi_0] = m\vec{E} , \\
& (\pm) [\tau_3 \partial_r \vec{\Phi} + \frac{1}{r} (\tau_1 \tau_2 - \tau_2 \tau_1) \vec{\Phi} + \\
& + \frac{1}{r} (\tau_1 \partial_\theta + \tau_2 \frac{\partial_\phi + \tau_3 \cos \theta}{\sin \theta}) \vec{\Phi}] = m\vec{H} .
\end{aligned} \tag{27}$$

From where with consideration of

$$\tau_1 \tau_2 - \tau_2 \tau_1 = \tau_3 , \quad \vec{e}_1 \tau_2 - \vec{e}_2 \tau_1 = 2\vec{e}_3 ,$$

we will have

$$\begin{aligned}
& \partial_0 C_0 - \vec{e}_3 (\partial_r + \frac{2}{r}) \vec{C} \\
& - \frac{1}{r} (\vec{e}_1 \partial_\theta + \vec{e}_2 \frac{\partial_\phi + \tau_3 \cos \theta}{\sin \theta}) \vec{C} = mC ,
\end{aligned} \tag{28}$$

$$\begin{aligned}
& \partial_0 C - \sigma \vec{e}_3 (\partial_r + \frac{2}{r}) \vec{E} \\
& - \frac{\sigma}{r} (\vec{e}_1 \partial_\theta + \vec{e}_2 \frac{\partial_\phi + \tau_3 \cos \theta}{\sin \theta}) \vec{E} = m C_0 , \\
& -\sigma \partial_0 \vec{E} + \vec{e}_3^t \partial_r C - \sigma \tau_3 (\partial_r + \frac{1}{r}) \vec{H} + \\
& + \frac{1}{r} (\vec{e}_1^t \partial_\theta + \vec{e}_2^t \frac{\partial_\phi}{\sin \theta}) C \\
& - \frac{\sigma}{r} (\tau_1 \partial_\theta + \tau_2 \frac{\partial_\phi + \tau_3 \cos \theta}{\sin \theta}) \vec{H} = m \vec{C} ,
\end{aligned} \tag{29}$$

$$\begin{aligned}
& \partial_0 C = m \Phi_0 , \\
& \vec{e}_3^t \partial_r C + \frac{1}{r} (\vec{e}_1^t \partial_\theta + \vec{e}_2^t \frac{\partial_\phi}{\sin \theta}) C = m \vec{\Phi} ,
\end{aligned} \tag{30}$$

$$\begin{aligned}
& (\pm) [\partial_0 \vec{\Phi} - \vec{e}_3^t \partial_r \Phi_0 \\
& - \frac{1}{r} (\vec{e}_1^t \partial_\theta + \vec{e}_2^t \frac{\partial_\phi}{\sin \theta}) \Phi_0] = m \vec{E} , \\
& (\pm) [\tau_3 (\partial_r + \frac{1}{r}) \vec{\Phi} \\
& + \frac{1}{r} (\tau_1 \partial_\theta + \tau_2 \frac{\partial_\phi + \tau_3 \cos \theta}{\sin \theta}) \vec{\Phi}] = m \vec{H} .
\end{aligned} \tag{31}$$

Now let us proceed to constructing eigen-functions of the operators $\vec{J}^2, J_3$. At this we will adhere to the well established procedure [15]. Allowing for the known defining relationships for Wigner D-functions [15]

$$\begin{aligned}
& -i \partial_\phi D_{-m,s}^j = m D_{-m,s}^j , \quad [-\frac{1}{\sin \theta} \partial_\theta \sin \theta \partial_\theta \\
& + \frac{m^2 + 2m\sigma \cos \theta + \sigma^2}{\sin^2 \theta}] D_{-m,s}^j = j(j+1) D_{-m,s}^j ,
\end{aligned}$$

we obtain the most general form of Ψ -function being eigen-functions of $\vec{J}^2$ and J_3 :

$$\begin{aligned}
& C(x) = e^{-ict} C(r) D_0 , \quad C_0(x) = +e^{-ict} C_0(r) D_0 , \quad \Phi_0(x) = e^{-ict} \Phi_0(r) D_0 , \\
& \vec{C}(x) = e^{-ict} \begin{vmatrix} C_1(r) D_{-1} \\ C_2(r) D_0 \\ C_3(r) D_{+1} \end{vmatrix} , \quad \vec{\Phi}(x) = e^{-ict} \begin{vmatrix} \Phi_1(r) D_{-1} \\ \Phi_2(r) D_0 \\ \Phi_3(r) D_{+1} \end{vmatrix} , \\
& \vec{E}(x) = e^{-ict} \begin{vmatrix} E_1(r) D_{-1} \\ E_2(r) D_0 \\ E_3(r) D_{+1} \end{vmatrix} , \quad \vec{H}(x) = e^{-ict} \begin{vmatrix} H_1(r) D_{-1} \\ H_2(r) D_0 \\ H_3(r) D_{+1} \end{vmatrix} ,
\end{aligned} \tag{32}$$

where the shorted notation $D_s = D_{-m,s}^j(\phi, \theta, 0)$, $s = 0, +1, -1$ is used. We will need several recurrent formulas [15]:

$$\begin{aligned}
\partial_\theta D_{-1} &= (1/2) (a D_{-2} - \nu D_0) , \\
\frac{-m + \cos \theta}{\sin \theta} D_{-1} &= (1/2) (-a D_{-2} - \nu D_0) , \\
\partial_\theta D_0 &= (1/2) (\nu D_{-1} - \nu D_{+1}) , \\
\frac{-m}{\sin \theta} D_0 &= (1/2) (-\nu D_{-1} - \nu D_{+1}) , \\
\partial_\theta D_{+1} &= (1/2) (\nu D_0 - a D_{+2}) , \\
\frac{-m - \cos \theta}{\sin \theta} D_{+1} &= (1/2) (-\nu D_0 - a D_{+2}) .
\end{aligned}$$

where

$$\nu = \sqrt{j(j+1)} , \quad a = \sqrt{(j-1)(j+2)} .$$

As a first step, one should obtain some intermediate relations:

$$\begin{aligned}
(\vec{e}_1 \partial_\theta + \vec{e}_2 \frac{\partial_\phi + \tau_3 \cos \theta}{\sin \theta}) \vec{C}(x) &= e^{-i\epsilon t} \frac{\nu}{\sqrt{2}} (C_1 + C_3) D_0 , \\
(\tau_1 \partial_\theta + \tau_2 \frac{\partial_\phi + \tau_3 \cos \theta}{\sin \theta}) \vec{H}(x) &= e^{-i\epsilon t} \frac{i\nu}{\sqrt{2}} \begin{vmatrix} -H_2 D_{-1} \\ (H_1 - H_3) D_0 \\ H_2 D_{+1} \end{vmatrix} , \\
(\vec{e}_1^t \partial_\theta + \vec{e}_2^t \frac{\partial_\phi}{\sin \theta}) C(x) &= -e^{-i\epsilon t} \frac{\nu}{\sqrt{2}} \begin{vmatrix} C D_{-1} \\ 0 \\ C D_{+1} \end{vmatrix} .
\end{aligned}$$

With the use of these we get to the following radial equations:

$$-i\epsilon C_0 - \left(\frac{d}{dr} + \frac{2}{r}\right)C_2 - \frac{\nu}{r}(C_1 + C_3) = mC . \quad (33)$$

$$\begin{aligned}
-i\epsilon C - \sigma\left(\frac{d}{dr} + \frac{2}{r}\right)E_2 - \frac{\nu\sigma}{r}(E_1 + E_3) &= mC_0 , \\
i\epsilon\sigma E_1 + \sigma\left(\frac{d}{dr} + \frac{1}{r}\right)H_1 - \frac{\nu}{r}C + \frac{i\nu\sigma}{r}H_2 &= mC_1 , \\
i\epsilon\sigma E_2 + \frac{d}{dr}C - \frac{i\nu\sigma}{r}(H_1 - H_3) &= mC_2 , \\
i\epsilon\sigma E_3 - \sigma\left(\frac{d}{dr} + \frac{1}{r}\right)H_3 - \frac{\nu}{r}C - \frac{i\nu\sigma}{r}H_2 &= mC_3 .
\end{aligned} \quad (34)$$

$$\begin{aligned}
-i\epsilon C &= m\Phi_0 , & -\frac{\nu}{r} C &= m\Phi_1 , \\
\frac{d}{dr} C &= m\Phi_2 , & -\frac{\nu}{r} C &= m\Phi_3 .
\end{aligned} \quad (35)$$

$$\begin{aligned}
(\pm)[-i\epsilon \Phi_1 + \frac{\nu}{r} \Phi_0] &= m E_1 , \\
(\pm)[-i\epsilon \Phi_2 - \frac{d}{dr} \Phi_0] &= m E_2 , \\
(\pm)[-i\epsilon \Phi_3 + \frac{\nu}{r} \Phi_0] &= m E_3 , \\
(\pm) [-i(\frac{d}{dr} + \frac{1}{r}) \Phi_1 - \frac{i\nu}{r} \Phi_2] &= m H_1 , \\
(\pm)\frac{i\nu}{r} (\Phi_1 - \Phi_3) &= m H_2 , \\
(\pm)[+i(\frac{d}{dr} + \frac{1}{r}) \Phi_3 + \frac{i\nu}{r} \Phi_2] &= m H_3 .
\end{aligned} \tag{36}$$

Where ν stands for $\sqrt{j(j+1)}/\sqrt{2}$.

4 Particle with polarizability in the Coulomb field

Taking into account the external Coulomb field can be done by means of one formal changing in the free particle radial system:

$$A_a = (\frac{ze}{r}, 0, 0, 0) , \quad \epsilon \implies (\epsilon + \frac{\alpha}{r}) , \quad \alpha = ze^2 .$$

As a result we have equations:

$$\begin{aligned}
-i(\epsilon + \frac{\alpha}{r})C_0 - (\frac{d}{dr} + \frac{2}{r}) C_2 \\
-\frac{\nu}{r} (C_1 + C_3) &= m C .
\end{aligned} \tag{37}$$

$$\begin{aligned}
-i(\epsilon + \frac{\alpha}{r}) C - \sigma (\frac{d}{dr} + \frac{2}{r}) E_2 \\
-\frac{\nu \sigma}{r} (E_1 + E_3) &= m C_0 , \\
i(\epsilon + \frac{\alpha}{r}) \sigma E_1 + \sigma (\frac{d}{dr} + \frac{1}{r}) H_1 \\
-\frac{\nu}{r} C + \frac{i \nu \sigma}{r} H_2 &= m C_1 , \\
i(\epsilon + \frac{\alpha}{r}) \sigma E_2 + \frac{d}{dr} C \\
-\frac{i \nu \sigma}{r} (H_1 - H_3) &= m C_2 , \\
i(\epsilon + \frac{\alpha}{r}) \sigma E_3 - \sigma (\frac{d}{dr} + \frac{1}{r}) H_3 \\
-\frac{\nu}{r} C - \frac{i \nu \sigma}{r} H_2 &= m C_3 .
\end{aligned} \tag{38}$$

$$\begin{aligned}
-i \left(\epsilon + \frac{\alpha}{r} \right) C &= m \Phi_0, \quad -\frac{\nu}{r} C = m \Phi_1, \\
\frac{d}{dr} C &= m \Phi_2, \quad -\frac{\nu}{r} C = m \Phi_3.
\end{aligned} \tag{39}$$

$$\begin{aligned}
(\pm)[-i(\epsilon + \frac{\alpha}{r})\Phi_1 + \frac{\nu}{r}\Phi_0] &= m E_1, \\
(\pm)[-i(\epsilon + \frac{\alpha}{r})\Phi_2 - \frac{d}{dr}\Phi_0] &= m E_2, \\
(\pm)[-i(\epsilon + \frac{\alpha}{r})\Phi_3 + \frac{\nu}{r}\Phi_0] &= m E_3, \\
(\pm)[-i(\frac{d}{dr} + \frac{1}{r})\Phi_1 - \frac{i\nu}{r}\Phi_2] &= m H_1, \\
(\pm)\frac{i\nu}{r}(\Phi_1 - \Phi_3) &= m H_2, \\
(\pm)[+i(\frac{d}{dr} + \frac{1}{r})\Phi_3 + \frac{i\nu}{r}\Phi_2] &= m H_3.
\end{aligned} \tag{40}$$

One should note these equations assume some additional conditions on radial functions:

$$\begin{aligned}
\Phi_3 &= + \Phi_1, \quad C_3 = + C_1, \\
E_3 &= + E_1, \quad H_3 = - H_1, \quad H_2 = 0.
\end{aligned} \tag{41}$$

Here, one interesting (from theoretical standpoint) fact should be emphasized. In considering analogous 15-component theory of a vector particle with polarizability (this work will be published separately) a discrete operator of P-inversion can be used to simplify the corresponding radial system. An idea is to rationalize the above conditions (41) in terms of this symmetry. So, let us try to diagonalize simultaneously with $\vec{J}^2, J_3$ else one, spatial inversion, operator. In initial Cartesian representation it is

$$\begin{aligned}
\hat{\Pi} &= 1 \oplus (1 \oplus -I) \oplus (1 \oplus -I) \oplus (-I \oplus +I) \hat{P}, \\
\hat{P}\Psi(\vec{r}) &= \Psi(-\vec{r}),
\end{aligned}$$

which after translating to the spherical tetrad and cyclic basis will look as

$$\begin{aligned}
\hat{\Pi} &= [1 \oplus (1 \oplus \Pi_3) \oplus (1 \oplus \Pi_3) \\
&\oplus (\Pi_3 \oplus -\Pi_3)] \hat{P}, \quad \Pi_3 = \begin{vmatrix} 0 & 0 & -1 \\ 0 & -1 & 0 \\ -1 & 0 & 0 \end{vmatrix}.
\end{aligned} \tag{42}$$

The proper values equation $\hat{\Pi}\Psi = P \Psi$ leads to solutions of two types:

$$\begin{aligned}
P &= (-1)^{j+1}, \\
C &= 0, \quad C_0 = 0, \quad C_3 = -C_1, \quad C_2 = 0, \\
\Phi_0 &= 0, \quad \Phi_3 = -\Phi_1, \quad \Phi_2 = 0, \\
E_3 &= -E_1, \quad E_2 = 0, \quad H_3 = H_1;
\end{aligned} \tag{43}$$

$$\begin{aligned}
P &= (-1)^j, \\
C_3 &= +C_1, \quad \Phi_3 = +\Phi_1, \\
E_3 &= +E_1, \quad H_3 = -H_1, \quad H_2 = 0.
\end{aligned} \tag{44}$$

We notice equations (44) coinciding with (41), which means that any solution of radial system provides us with a state of definite parity $P = (-1)^j$. In turn, it is readily verified that another set of restrictions (44), being applied to the above radial system, will lead to a inconsistent equations. Such behavior is just what it must be expected for a spin 0 particle.

Let us proceed with radial system. With the use of (41) it will take the form

$$-i(\epsilon + \frac{\alpha}{r})C_0 - (\frac{d}{dr} + \frac{2}{r})C_2 - \frac{\nu}{r}2C_1 = mC; \tag{45}$$

$$\begin{aligned}
-i(\epsilon + \frac{\alpha}{r})C - \sigma(\frac{d}{dr} + \frac{2}{r})E_2 - \frac{\nu\sigma}{r}2E_1 &= mC_0, \\
i(\epsilon + \frac{\alpha}{r})\sigma E_1 + \sigma(\frac{d}{dr} + \frac{1}{r})H_1 - \frac{\nu}{r}C &= mC_1, \\
i(\epsilon + \frac{\alpha}{r})\sigma E_2 + \frac{d}{dr}C - \frac{i\nu\sigma}{r}2H_1 &= mC_2;
\end{aligned} \tag{46}$$

$$\begin{aligned}
-i(\epsilon + \frac{\alpha}{r})C &= m\Phi_0, \quad -\frac{\nu}{r}C = m\Phi_1, \\
\frac{d}{dr}C &= m\Phi_2;
\end{aligned} \tag{47}$$

$$\begin{aligned}
(\pm)[-i(\epsilon + \frac{\alpha}{r})\Phi_1 + \frac{\nu}{r}\Phi_0] &= mE_1, \\
(\pm)[-i(\epsilon + \frac{\alpha}{r})\Phi_2 - \frac{d}{dr}\Phi_0] &= mE_2, \\
(\pm)[-i(\frac{d}{dr} + \frac{1}{r})\Phi_1 - \frac{i\nu}{r}\Phi_2] &= mH_1.
\end{aligned} \tag{48}$$

Substituting expressions for C_i from (47) into (48), one finds

$$E_1 = 0, \quad E_2 = (\pm)(-\frac{i\alpha}{m^2 r^2})C, \quad H_1 = 0. \tag{49}$$

Now, allowing for (49), one produces

$$\begin{aligned}
mC_0 &= -i(\epsilon + \frac{\alpha}{r}) \pm \frac{i\alpha\sigma}{m^2 r^2} \frac{dC}{dr}, \\
mC_1 &= -\frac{\nu}{r}C, \quad mC_2 = \frac{dC}{dr} \pm \frac{\alpha\sigma}{m^2 r^2}C.
\end{aligned} \tag{50}$$

And finally, with (50), from (45), we arrive at an equation for $C(r)$ (changing m^2 to $-M^2$, and $2\nu^2$ to $j(j+1)$):

$$\frac{d^2}{dr^2} C + \frac{2}{r} \frac{d}{dr} C + \left[\left(\epsilon + \frac{\alpha}{r} \right)^2 - M^2 - \frac{j(j+1)}{r^2} \pm \frac{\sigma\alpha^2}{M^2 r^4} \right] C(r) = 0 . \quad (51)$$

This differential equation describes a scalar particle with polarizability in external Coulomb field.

5 Particle in the external magnetic monopole field

Now we investigate the scalar particle with polarizability in presence of Dirac magnetic monopole field, adhering the technics developed in the previous Section. Here, the main equation is

$$[\Gamma^\alpha(x) (\partial_\alpha + B_\alpha - i \frac{e}{\hbar c} A_\alpha) - \frac{mc}{\hbar}] \Psi(x) = 0 ,$$

where 4-vector is determined as (the form of Schwinger monopole potential is used [17], which has been transformed to spherical coordinates $x^\alpha = (x^0, r, \theta, \phi)$)

$$A_\alpha = (0, 0, 0, A_\phi = g \cos \theta) ,$$

g stands for a magnetic charge. All difference from the task in previous section consists in one formal change

$$\partial_\phi \implies (\partial_\phi + i k \cos \theta) , \quad \text{where} \quad k = \frac{e g}{\hbar c} .$$

Correspondingly the wave equation leads to

$$\left[\Gamma^0 \partial_0 + \Gamma^3 \partial_r + \frac{\Gamma^1 J^{31} + \Gamma^2 J^{32}}{r} + \frac{1}{r} \Sigma_{\theta, \phi}^k - m \right] \Psi = 0 , \quad (52)$$

where a modified θ, ϕ -dependent operator is defined by

$$\Sigma_{\theta, \phi}^k = \Gamma^1 \partial_\theta + \Gamma^2 \frac{\partial_\phi + (J^{12} + ik) \cos \theta}{\sin \theta} . \quad (53)$$

Most calculation from previous section is not to be repeated here, we can momentarily proceed to evidently modified equations of the type (27):

$$\begin{aligned} & \partial_0 C_0 - \vec{e}_3 \left(\partial_r + \frac{2}{r} \right) \vec{C} - \\ & - \frac{1}{r} (\vec{e}_1 \partial_\theta + \vec{e}_2 \frac{\partial_\phi + (\tau_3 + ik) \cos \theta}{\sin \theta}) \vec{C} = m C , \end{aligned} \quad (54)$$

$$\begin{aligned}
& \partial_0 C - \sigma \vec{e}_3 (\partial_r + \frac{2}{r}) \vec{E} - \\
& - \frac{\sigma}{r} (\vec{e}_1 \partial_\theta + \vec{e}_2 \frac{\partial_\phi + (\tau_3 + ik) \cos \theta}{\sin \theta}) \vec{E} = m C_0 , \\
& - \sigma \partial_0 \vec{E} + \vec{e}_3^t \partial_r C - \sigma \tau_3 (\partial_r + \frac{1}{r}) \vec{H} + \\
& + \frac{1}{r} (\vec{e}_1^t \partial_\theta + \vec{e}_2^t \frac{\partial_\phi + ik \cos \theta}{\sin \theta}) C - \\
& - \frac{\sigma}{r} (\tau_1 \partial_\theta + \tau_2 \frac{\partial_\phi + (\tau_3 + ik) \cos \theta}{\sin \theta}) \vec{H} = m \vec{C} ,
\end{aligned} \tag{55}$$

$$\begin{aligned}
& \partial_0 C = m \Phi_0 , \quad \vec{e}_3^t \partial_r C \\
& + \frac{1}{r} (\vec{e}_1^t \partial_\theta + \vec{e}_2^t \frac{\partial_\phi + ik \cos \theta}{\sin \theta}) C = m \vec{\Phi} ,
\end{aligned} \tag{56}$$

$$\begin{aligned}
& (\pm) [\partial_0 \vec{\Phi} - \vec{e}_3^t \partial_r \Phi_0 \\
& - \frac{1}{r} (\vec{e}_1^t \partial_\theta + \vec{e}_2^t \frac{\partial_\phi + ik \cos \theta}{\sin \theta}) \Phi_0] = m \vec{E} , \\
& (\pm) [\tau_3 (\partial_r + \frac{1}{r}) \vec{\Phi} \\
& + \frac{1}{r} (\tau_1 \partial_\theta + \tau_2 \frac{\partial_\phi + (\tau_3 + ik) \cos \theta}{\sin \theta}) \vec{\Phi}] = m \vec{H} .
\end{aligned} \tag{57}$$

Now it is the point to choose a suitable substitution for a wave function Ψ , that might allow for definite symmetry properties of the system in presence of monopole. There exist three operators satisfying SO(3.R) commutation relations:

$$\begin{aligned}
J_1^{(k)} &= l_1 + \frac{\cos \phi}{\sin \theta} (S_3 - k) , \\
J_2^{(k)} &= l_2 + \frac{\sin \phi}{\sin \theta} (S_3 - k), \quad J_3^{(k)} = l_3 .
\end{aligned} \tag{58}$$

Therefore

$$\begin{aligned}
J_3^{(k)} &= l_3 , \quad \vec{J}_{(k)}^2 = - \frac{1}{\sin \theta} \partial_\theta \sin \theta \partial_\theta + \\
& + \frac{-\partial_\phi^2 + 2 i \partial_\phi (S_3 - k) \cos \theta + (S_3 - k)_3^2}{\sin^2 \theta} .
\end{aligned}$$

A most general wave function with properties

$$\vec{J}_{(k)}^2 \Psi_{jm}^{(k)} = j(j+1) \Psi_{jm}^{(k)} , \quad J_3^{(k)} \Psi_{jm}^{(k)} = m \Psi_{jm}^{(k)} .$$

has the structure

$$\begin{aligned}
\Psi(x) &= \{ C(x), C_0(x), \vec{C}(x), \Phi_0(x), \vec{\Phi}(x), \vec{E}(x), \vec{H}(x) \} , \\
C(x) &= e^{-i\epsilon t} C(r) D_k , \quad C_0(x) = e^{-i\epsilon t} C_0(r) D_k , \quad \Phi_0(x) = e^{-i\epsilon t} \Phi_0(x) D_k , \\
\vec{C}(x) &= e^{-i\epsilon t} \begin{vmatrix} C_1 D_{k-1} \\ C_2 D_k \\ C_3 D_{k+1} \end{vmatrix} , \quad \vec{\Phi}(x) = e^{-i\epsilon t} \begin{vmatrix} \Phi_1 D_{k-1} \\ \Phi_2 D_k \\ \Phi_3 D_{k+1} \end{vmatrix} , \\
\vec{E}(x) &= e^{-i\epsilon t} \begin{vmatrix} E_1 D_{k-1} \\ E_2 D_k \\ E_3 D_{k+1} \end{vmatrix} , \quad \vec{H}(x) = e^{-i\epsilon t} \begin{vmatrix} H_1 D_{k-1} \\ H_2 D_k \\ H_3 D_{k+1} \end{vmatrix} , \quad (59)
\end{aligned}$$

where

$$D_s = D_{-m,s}^j(\phi, \theta, 0) , \quad s = k, k+1, k-1 .$$

With the use of recursive formulas [15]

$$\begin{aligned}
\partial_\theta D_{\kappa-1} &= (a D_{\kappa-2} - c D_\kappa) , \\
\frac{-m - (\kappa - 1) \cos \theta}{\sin \theta} D_{\kappa-1} &= (-a D_{\kappa-2} - c D_\kappa) , \\
\partial_\theta D_\kappa &= (c D_{\kappa-1} - d D_{\kappa+1}) , \\
\frac{-m - \kappa \cos \theta}{\sin \theta} D_\kappa &= (-c D_{\kappa-1} - d D_{\kappa+1}) , \\
\partial_\theta D_{\kappa+1} &= (d D_\kappa - b D_{\kappa+2}) , \\
\frac{-m - (\kappa + 1) \cos \theta}{\sin \theta} D_{\kappa+1} &= (-d D_\kappa - b D_{\kappa+2}) ,
\end{aligned}$$

where

$$\begin{aligned}
a &= \frac{1}{2} \sqrt{(j + \kappa - 1)(j - \kappa + 2)} , \\
b &= \frac{1}{2} \sqrt{(j - \kappa - 1)(j + \kappa + 2)} , \\
c &= \frac{1}{2} \sqrt{(j + \kappa)(j - \kappa + 1)} , \\
d &= \frac{1}{2} \sqrt{(j - \kappa)(j + \kappa + 1)} ,
\end{aligned}$$

one finds

$$\begin{aligned}
[\vec{e}_1 \partial_\theta + \vec{e}_2 \frac{\partial_\phi + (\tau_3 + i k) \cos \theta}{\sin \theta}] \vec{C} &= e^{-i\epsilon t} \sqrt{2} (c C_1 + d C_3) D_k , \\
\tau_1 \partial_\theta \vec{H} + \tau_2 \frac{\partial_\phi + (\tau_3 + i k) \cos \theta}{\sin \theta} \vec{H} &= e^{-i\epsilon t} (i\sqrt{2}) \begin{vmatrix} -c H_2 D_{k-1} \\ (c H_1 - d H_3) D_k \\ +d H_2 D_{k+1} \end{vmatrix} , \\
(\vec{e}_1^t \partial_\theta + \vec{e}_2^t \frac{\partial_\phi + i k \cos \theta}{\sin \theta}) C &= e^{-i\epsilon t} e^{-i\epsilon t} \sqrt{2} \begin{vmatrix} -c C(r) D_{k-1} \\ 0 \\ -d C(r) D_{k+1} \end{vmatrix} .
\end{aligned}$$

After simple calculation one arrives at

$$-i\epsilon C_0 - \left(\frac{d}{dr} + \frac{2}{r}\right)C_2 - \frac{1}{r}\sqrt{2}(cC_1 + dC_3) = mC ; \quad (60)$$

$$\begin{aligned} -i\epsilon C - \sigma\left(\frac{d}{dr} + \frac{2}{r}\right)E_2 - \frac{\sigma}{r}\sqrt{2}(cE_1 + dE_3) &= mC_0 , \\ i\epsilon\sigma E_1 + \sigma\left(\frac{d}{dr} + \frac{1}{r}\right)H_1 - \frac{\sqrt{2}c}{r}C + \frac{\sigma}{r}(i\sqrt{2}c)H_2 &= mC_1 , \\ i\epsilon\sigma E_2 + \frac{d}{dr}C - \frac{\sigma}{r}(i\sqrt{2})(cH_1 - dH_3) &= mC_2 , \\ i\epsilon\sigma E_3 - \sigma\left(\frac{d}{dr} + \frac{1}{r}\right)H_3 - \frac{\sqrt{2}d}{r}C - \frac{\sigma}{r}(i\sqrt{2}d)H_2 &= mC_3 ; \end{aligned} \quad (61)$$

$$\begin{aligned} -i\epsilon C &= m\Phi_0 , & -\frac{\sqrt{2}c}{r}C &= m\Phi_1 , \\ \frac{d}{dr}C &= m\Phi_2 , & -\frac{\sqrt{2}d}{r}C &= m\Phi_3 ; \end{aligned} \quad (62)$$

$$\begin{aligned} (\pm)[-i\epsilon\Phi_1 + \frac{\sqrt{2}c}{r}\Phi_0] &= mE_1 , \\ (\pm)[-i\epsilon\Phi_2 - \frac{d}{dr}\Phi_0] &= mE_2 , \\ (\pm)[-i\epsilon\Phi_3 + \frac{\sqrt{2}d}{r}\Phi_0] &= mE_3 , \\ (\pm)[-i\left(\frac{d}{dr} + \frac{1}{r}\right)\Phi_1 - \frac{i\sqrt{2}c}{r}\Phi_2] &= mH_1 , \\ (\pm)(i\sqrt{2})\frac{1}{r}(c\Phi_1 - d\Phi_3) &= mH_2 , \\ (\pm)[+i\left(\frac{d}{dr} + \frac{1}{r}\right)\Phi_3 + \frac{i\sqrt{2}d}{r}\Phi_2] &= mH_3 . \end{aligned} \quad (63)$$

Our aim is a final single differential equation for $C(r)$. As a first step, expressions for $\Phi_a(r)$ from (62) are to be entered equation (63):

$$\begin{aligned} m^2 E_1 &= (\pm)[(i\epsilon)\left(\frac{1}{r}\right)\sqrt{2}cC + \frac{\sqrt{2}c}{r}(-i\epsilon)C] = 0 , \\ m^2 E_2 &= (\pm)[-i\epsilon\frac{d}{dr}C - \frac{d}{dr}(-i\epsilon)C] = 0 , \\ mE_3 &= (\pm)[i\epsilon\frac{\sqrt{2}c}{r}C + \frac{\sqrt{2}c}{r}(-i\epsilon)C] = 0 . \end{aligned}$$

Further, let us substitute $\Phi_a(r)$ from (62) into (63):

$$\begin{aligned}
m^2 H_1 &= (\pm) \left[-i \left(\frac{d}{dr} + \frac{1}{r} \right) \left(-\frac{1}{r} \right) \sqrt{2} c C + \frac{1}{r} (-i \sqrt{2} c) \frac{d}{dr} C \right] = 0 , \\
m^2 H_2 &= (\pm) \frac{1}{r} (i \sqrt{2}) \left[-c \frac{1}{r} \sqrt{2} c C + d \frac{\sqrt{2} d}{r} C \right] = \\
&= (\pm) \frac{2i}{r^2} (d^2 - c^2) C = (\pm) (-i) \frac{k}{r^2} C , \\
m^2 H_3 &= (\pm) \left[-i \left(\frac{d}{dr} + \frac{1}{r} \right) \frac{1}{r} \sqrt{2} d C + \frac{i d \sqrt{2}}{r} \frac{d}{dr} C \right] = 0 .
\end{aligned}$$

Therefore

$$\begin{aligned}
E_1 &= 0 , \quad E_2 = 0 , \quad E_3 = 0 , \quad H_1 = 0 , \\
H_2 &= (\pm) (-i) \frac{k}{m^2 r^2} C , \quad H_3 = 0 ,
\end{aligned} \tag{64}$$

which being taken into equations (61) give for $C_a(r)$:

$$\begin{aligned}
m C_0 &= -i \epsilon C , \quad m C_1 = -\frac{\sqrt{2} c}{r} C \pm \sigma \frac{\sqrt{2} c}{r} \frac{k}{m^2 r^2} C , \\
m C_2 &= \frac{d}{dr} C , \quad m C_3 = -\frac{\sqrt{2} d}{r} C \mp \sigma \frac{\sqrt{2} d}{r} \frac{k}{m^2 r^2} C .
\end{aligned} \tag{65}$$

Finally, with the use of (5.18), we arrive at $C(r)$:

$$\begin{aligned}
&\frac{d^2}{dr^2} C + \frac{2}{r} \frac{d}{dr} C + [\epsilon^2 + m^2 - \\
&- \frac{2(c^2 + d^2)}{r^2} \pm \sigma \frac{k}{m^2 r^4} 2(c^2 - d^2)] C = 0 .
\end{aligned}$$

From this, taking the formulas

$$c^2 - d^2 = \frac{k}{2}, \quad c^2 + d^2 = \frac{j(j+1) - k^2}{2}, \quad m^2 = -M^2 ,$$

one gets a differential equation for $C(r)$

$$\begin{aligned}
&\frac{d^2}{dr^2} C + \frac{2}{r} \frac{d}{dr} C + [\epsilon^2 - M^2 \\
&- \frac{j(j+1) - k^2}{r^2} \mp \sigma \frac{k^2}{M^2 r^4}] C = 0
\end{aligned} \tag{66}$$

where the term proportional to σ -parameter describes peculiarity supplied by additional electromagnetic structure of a scalar particle — polarizability. It should be specially noted that because of the known singular properties of a r^{-4} potential in Shrödinger problem the influence of the monopole on a scalar particle with polarizability will be much more significant than in the case of ordinary scalar particle; the latter formally follows from (66) on making $\sigma = 0$ and vanishing r^{-4} term.

6 Particle in presence of both electric and magnetic charges

Now we consider behavior of a scalar particle with polarizability in presence both of a Coulomb potential and Dirac monopole one. One does not need to perform much calculation in addition to yet done in previous sections. It suffices to make one formal change in radial equation of previous Section:

$$\epsilon \quad \Longrightarrow \quad \left(\epsilon + \frac{\alpha}{r} \right) .$$

As result, one gets

$$\begin{aligned} & -i \left(\epsilon + \frac{\alpha}{r} \right) C_0 - \left(\frac{d}{dr} + \frac{2}{r} \right) C_2 \\ & - \frac{1}{r} \sqrt{2} (c C_1 + d C_3) = m C ; \end{aligned} \tag{67}$$

$$\begin{aligned} & -i \left(\epsilon + \frac{\alpha}{r} \right) C - \sigma \left(\frac{d}{dr} + \frac{2}{r} \right) E_2 \\ & - \frac{\sigma}{r} \sqrt{2} (c E_1 + d E_3) = m C_0 , \\ & i \left(\epsilon + \frac{\alpha}{r} \right) \sigma E_1 + i \sigma \left(\frac{d}{dr} + \frac{1}{r} \right) H_1 \\ & - \frac{\sqrt{2} c}{r} C + \frac{\sigma}{r} (i \sqrt{2} c) H_2 = m C_1 , \\ & i \left(\epsilon + \frac{\alpha}{r} \right) \sigma E_2 + \frac{d}{dr} C \\ & - \frac{\sigma}{r} (i \sqrt{2}) (c H_1 - d H_3) = m C_2 , \\ & i \left(\epsilon + \frac{\alpha}{r} \right) \sigma E_3 - i \sigma \left(\frac{d}{dr} + \frac{1}{r} \right) H_3 \\ & - \frac{\sqrt{2} d}{r} C - \frac{\sigma}{r} (i \sqrt{2} d) H_2 = m C_3 ; \end{aligned} \tag{68}$$

$$\begin{aligned} & -i \left(\epsilon + \frac{\alpha}{r} \right) C = m \Phi_0 , \quad -\frac{\sqrt{2} c}{r} C = m \Phi_1 , \\ & \frac{d}{dr} C = m \Phi_2 , \quad -\frac{\sqrt{2} d}{r} C = m \Phi_3 ; \end{aligned} \tag{69}$$

$$\begin{aligned}
(\pm)[-i(\epsilon + \frac{\alpha}{r})\Phi_1 + \frac{\sqrt{2}c}{r}\Phi_0] &= mE_1, \\
(\pm)[-i(\epsilon + \frac{\alpha}{r})\Phi_2 - \frac{d}{dr}\Phi_0] &= mE_2, \\
(\pm)[-i(\epsilon + \frac{\alpha}{r})\Phi_3 + \frac{\sqrt{2}d}{r}\Phi_0] &= mE_3, \\
(\pm)[-i(\frac{d}{dr} + \frac{1}{r})\Phi_1 - \frac{i\sqrt{2}c}{r}\Phi_2] &= mH_1, \\
(\pm)(i\sqrt{2})\frac{1}{r}(c\Phi_1 - d\Phi_3) &= mH_2, \\
(\pm)[+i(\frac{d}{dr} + \frac{1}{r})\Phi_3 + \frac{i\sqrt{2}d}{r}\Phi_2] &= mH_3.
\end{aligned} \tag{70}$$

Substituting expressions for $\Phi_a(r)$ from (69) into eqs. (70):

$$\begin{aligned}
m^2 E_1 &= (\pm) \left[\left(i \left(\epsilon + \frac{\alpha}{r} \right) \right) \left(\frac{1}{r} \right) \sqrt{2} c C + \frac{\sqrt{2} c}{r} \left(-i \left(\epsilon + \frac{\alpha}{r} \right) \right) C \right] = 0, \\
m^2 E_2 &= (\pm) \left[-i \left(\epsilon + \frac{\alpha}{r} \right) \frac{d}{dr} C - \frac{d}{dr} \left(-i \left(\epsilon + \frac{\alpha}{r} \right) \right) C \right] = \pm i \frac{(-\alpha)}{r^2} C, \\
m E_3 &= (\pm) \left[i \left(\epsilon + \frac{\alpha}{r} \right) \frac{\sqrt{2} d}{r} C + \frac{\sqrt{2} d}{r} \left(-i \left(\epsilon + \frac{\alpha}{r} \right) \right) C \right] = 0.
\end{aligned}$$

Expressions for $\Phi_a(r)$ from are to be substituted into (70):

$$\begin{aligned}
m^2 H_1 &= (\pm) \left[-i \left(\frac{d}{dr} + \frac{1}{r} \right) \left(-\frac{1}{r} \right) \sqrt{2} c C + \frac{1}{r} \left(-i\sqrt{2}c \right) \frac{d}{dr} C \right] = 0, \\
m^2 H_2 &= (\pm) \frac{1}{r} (i\sqrt{2}) \left[-c \frac{1}{r} \sqrt{2} c + d \frac{\sqrt{2}d}{r} \right] C = \pm \left(\frac{-ieg}{m^2 r^2} \right) C, \\
m^2 H_3 &= \pm \left[-i \left(\frac{d}{dr} + \frac{1}{r} \right) \frac{1}{r} \sqrt{2} d + \frac{id\sqrt{2}}{r} \frac{d}{dr} C \right] = 0.
\end{aligned}$$

Thus, for $E_i(r), H_i(r)$ we get to

$$\begin{aligned}
E_1 &= 0, \quad E_2 = (\pm) \frac{-i \alpha}{m^2 r^2} C, \quad E_3 = 0, \\
H_1 &= 0, \quad H_2 = (\pm) \frac{-i eg}{m^2 r^2} C, \quad H_3 = 0.
\end{aligned} \tag{71}$$

Accounting (71), from (68) one obtains expressions for $C_a(r)$:

$$\begin{aligned}
mC_0 &= -i \left(\epsilon + \frac{\alpha}{r} \right) C - \sigma \left(\frac{d}{dr} + \frac{2}{r} \right) (\pm) \frac{-i\alpha}{m^2 r^2} C, \\
mC_1 &= -\frac{\sqrt{2}c}{r} C \pm \sigma \frac{\sqrt{2}c}{r} \frac{(-ieg)}{m^2 r^2} C, \\
mC_2 &= \frac{d}{dr} C + \sigma i \left(\epsilon + \frac{\alpha}{r} \right) (\pm) \frac{-i\alpha}{m^2 r^2} C, \\
mC_3 &= -\frac{\sqrt{2}d}{r} C \pm \sigma \frac{\sqrt{2}d}{r} \frac{ieg}{m^2 r^2} C.
\end{aligned}$$

(72)

And finally, with (72), from (67) we arrive at a differential equation for $C(r)$:

$$\begin{aligned}
& -i\left(\epsilon + \frac{\alpha}{r}\right)\left(-i\left(\epsilon + \frac{\alpha}{r}\right) C\right. \\
& \left. - \sigma\left(\frac{d}{dr} + \frac{2}{r}\right)(\pm)\frac{-i\alpha}{m^2 r^2} C\right) - \\
& -\left(\frac{d}{dr} + \frac{2}{r}\right)(\pm\sigma)\left(\epsilon + \frac{\alpha}{r}\right)\frac{\alpha}{m^2 r^2} C + \frac{dC}{dr} - \\
& -\frac{\sqrt{2}}{r}\left(c\left(-\frac{\sqrt{2}c}{r} C \pm \frac{i\sqrt{2}c}{r}\frac{\sigma(-ieg)}{m^2 r^2} C\right) + \right. \\
& \left. + d\left(-\frac{\sqrt{2}d}{r} C \pm \frac{i\sqrt{2}d\sigma}{r}\frac{(+ieg)}{m^2 r^2} C\right) = m^2 C
\end{aligned}$$

or

$$\begin{aligned}
& -\left(\epsilon + \frac{\alpha}{r}\right)^2 C \pm \frac{\sigma\alpha^2}{m^2 r^4} C - \left(\frac{d}{dr} + \frac{2}{r}\right)\frac{dC}{dr} + \\
& + \frac{2}{r^2}(d^2 + c^2)C \pm \frac{2\sigma eg(d^2 - c^2)}{m^2 r^4} C = m^2 C .
\end{aligned} \tag{73}$$

Eq. (73), with the use of (also $m^2 = -M^2$)

$$c^2 - d^2 = -\frac{k}{2}, c^2 + d^2 = \frac{j(j+1) - k^2}{2},$$

will take the form

$$\begin{aligned}
& \frac{d^2}{dr^2} C + \frac{2}{r} \frac{d}{dr} C + \left[\left(\epsilon + \frac{\alpha}{r}\right)^2 - M^2 \right. \\
& \left. - \frac{j(j+1) - k^2}{r^2} \pm \sigma \frac{e^4 - k^2}{M^2 r^4} \right] C = 0 .
\end{aligned} \tag{74}$$

The structure of the obtained equation permits by means of deliberate fitting values α and k to have $\alpha^2 = k^2$, what means that in equation (74) the singular term r^{-4} vanishes.

References

- [1] Fedorov F.I., Pletjuchov V.A. Vesti AN BSSR. Ser. fiz.-mat. 1969. No 6. P. 81-88; 1970. No 3. P. 78-83.
- [2] Pletjuchov V.A., Fedorov F.I. Vesti AN BSSR. Ser. fiz.-mat. 1970. No 2. P. 79-85; 1970. No 3. P. 84-92.
- [3] A.A. Bogush, V.V. Kisel. Vesti AN BSSR. Ser. fiz.-mat. 1979. No 3. P. 61-65 (in Russian).

- [4] A.A. Bogush, V.V. Kisel, M.I. Levchuk, L.G. Moroz. In: Covariant methods in theoretical physics. Elementary particle physics and relativity theory. Institute of Physics, Academy of sciences of Belarus. Minsk. 1981. P. 81-90.
- [5] V.V. Kisel. Vesti AN BSSR. Ser. fiz.-mat. 1982. No 3. P. 73-78 (in Russian).
- [6] A.A. Bogush, V.V. Kisel. Doklady AN BSSR. 1984. Vol. 28. No 8. P. 702-705 (in Russian).
- [7] A.A. Bogush, V.V. Kisel. Izvestiya VUZ. Fizika. 1984. No 1. P. 23-27 (in Russian).
- [8] A.A. Bogush, V.V. Kisel, F.I. Fedorov. Doklady AN BSSR. 1984. Vol. 277. No 2. P. 343-346 (in Russian).
- [9] Bogush A.A., Kisel V.V., Tokarevskaya N.G., Red'kov V.M. Vesti AN BSSR. Ser. Fiz.-Mat. Navuk. 2001, No 3. P. 65-71.
- [10] Kisel V.V., Tokarevskaya N.G., Red'kov V.M. Preprin 730, Institute of Physics of National Academy of Sciences of Belarus. Minsk. 2001, 25 pages (in Russian).
- [11] Tetrode H. Z. Phys. 1928. Bd 50. S.
- [12] Weyl H. Proc. Nat. Acad. Sci. Amer. 1929. Vol. 15. P. 323 -334; Rice Inst. Pamphlet. 1929. Vol. 16. P. 280-295; Z. Phys. 1929. Bd 56. S. 330-352.
- [13] Fock V., Ivanenko D. Z. Phys. 1929. Bd 54. S. 798-802; Compt. Rend. Acad. Sci. Paris. 1929. Vol. 188. P. 1470-1472.
- [14] Fock V. Z. Phys. 1929. Bd 57. S. 261-277.
- [15] Varshalovich D.A., Moskalev A.N., Xersonskiy V.K. *Quantum theory of angular momentum*. Leningrad. 1975.
- [16] Bogush A.A., Otchik V.S., Red'kov V.M. Preprint 426, Institut of Physics, AN BSSR. Minsk, 1986. 44 pages (in Russian).
- [17] Strajev V.I., Tomilchik L.M. *Electrodynamics with magnetic charge*. Minsk. 1975.